



Communications Systems, Inc.

“We Provide Voice & Data Networking Solutions”

www.computelnj.com

Computel Communications Systems, Inc. Support Documentation

Note: This document is solely intended to support customers of Computel Communications Systems, Inc. Duplication without written consent of Computel Communications System is strictly prohibited

Changing the Time and Date

Feature **time (8463)
Password: admin (23646)
Hour: 10 : press change softkey, enter new hour
Press next softkey
Minutes: 04: press change softkey, enter new minutes
Press next softkey
Year 06: enter two digit year
Press next softkey
Month: 02: enter two digit month
Press next softkey
Day: enter two digit day
--End of list—
Press rls button to exit

Or:

Feature **266344
Password 266344
Terminals & Sets> Next (bottom right arrow) until you see Time&Date
Time & Date> Show (top right arrow)
Hour: use the Change softkey
Minute: use the Change softkey
Year: use the Change softkey
Month: use the Change softkey
Day: use the Change softkey
Once you have the correct time and date use the RLS key to end the session.